#### **DOE OFFICE OF INDIAN ENERGY**


# The Five-Step Development Process Step 1: Identify Project Potential





## **Presentation Agenda**

- Brief Review of Day 1
- Step 1: Identifying Project Potential
  - Community Market Potential
  - Resource Potential
  - Initial Site Considerations
- Tools and Resources
- Small Group Exercise/Discussion





#### Step 1: Site, Scale, Resource, and Community Market Potential



Purpose: Determine whether basic elements for a successful project are in place

#### Tasks:

- 1. Identify possible **sites** for project locations
- 2. Determine the **energy load/demand** for these sites using past electric bills for these facilities
- 3. Confirm renewable energy resource
- 4. Review tribal facility electric cost data, regulations, and transmission and interconnection requirements
- 5. Evaluate community market potential for renewable sales. Your community is the marketplace/energy user
- 6. Assemble or communicate with the right team—those in positions or with knowledge to facilitate, approve, and champion the project



# **Understanding Community Market Potential**

#### Who is your market?

Tribal community

#### What do you need to know?

- Current energy loads and demand
- Expected future energy loads and demand of the system
- Condition of buildings and availability of roof space and land
- Consider energy efficiency/weatherization first (typically the most cost-effective)

	2015	2016	2017
Energy (kWh)			
Demand (avg kW)			

## Sizing Your Renewable Energy System

#### **Current Load**

- Use your past monthly energy bills to determine the demand. Start with your strategic energy plan
- Consider your scale: residential, commercial, or industrial
- Consider the current tariff structure (how the energy is metered and billed)

#### **Future Load**

- At which energy scale does your community expect the most growth in energy demand?
- How much will you need?

#### Other Limiting Factors

- Interconnection
- Net metering cap
- Rebate limits

	2015	2017	2019
Energy (kWh)	XYZ	XYZ	XYZ
Demand (avg kW)	XYZ	XYZ	XYZ



# Resource, Production & Savings


# Assess available local energy resources

# Production

- Online tools (PV Watts)
- Field based measuring equipment
- Resource maps




# Solar PV Energy Resource Mapping






#### Solar Resources in Oklahoma






# Wind Energy Resource Mapping: 30 Meter (m)






# Wind Energy Resource Mapping: 80 m






#### Wind Resources in Oklahoma






## Biomass Energy Resource Mapping: Crop Residues






# Biomass Energy Resource Mapping: Wood






#### **Biomass Resources in Oklahoma**






# **Tribal Partnership Opportunities**




Source: http://en.wikipedia.org/wiki/Oklahoma\_Tribal\_Statistical\_Area



### **Local Site Considerations**




### **Local Site Considerations — Urban Centers**






## **Local Site Considerations — Rivers**






## **Local Site Considerations — Road Access**





## **Local Site Considerations — Suitable Area**





# **Initial Site Considerations — Example**




# Initial Solar Site Considerations — Slope>1%






# Initial Solar Site Considerations — Slope > 5%






# Initial Wind Site Considerations — Slope>20%



# **Wind Siting Obstructions**



Source: OpenEI, http://en.openei.org/wiki/File:ObstructionOfWindByBuilding.png



## **Initial Biomass Siting Considerations**

#### Potential resource; determine:

- Local suppliers and equipment
- Quantities available (including long-term)
- Cost
- Quality
  - Sufficient volume
  - Future availability
  - Control (long-term purchase agreement)
- Distance (transportation cost)

#### Check permitting requirements:

- Air permits
- Ash disposal
- Fire permits



Photo from Mississippi Band of Choctaw Indians, NREL 26448



Photo from Randy Hunsberger, NREL



## **Initial Biomass Siting Considerations**

#### Space requirements

- Ensure sufficient space for biomass boiler in boiler room
- Determine fuel requirements and storage space available
- Evaluate truck access, including space for maneuvering



Photo by Randy Hunsberger, NREL



#### **Priorities: Where to Install Solar**

- On the "built environment" where unshaded:
  - Existing building roofs that have an expected life of at least 15 more years and can accept added load typically 2-4 pounds /ft².
     Reduces solar load on building
  - All new buildings all new buildings should be "solar ready
    - See Solar Ready Buildings Planning Guide: <a href="http://www.nrel.gov/docs/fy10osti/46078.pdf">http://www.nrel.gov/docs/fy10osti/46078.pdf</a>
  - Over parking areas energy generation and nice amenity
- On compromised lands such as landfills and brownfields
  - Saves green-fields for nature
  - If installed on green fields, minimize site disturbance; plant native low height vegetation as needed



## **Solar PV Placement**



PV Panels on Grand Ronde Tribal Housing Authority carport. Photo by GRTHA, NREL 11659046



Facility Scale Hybrid System, NPS Range Station, San Miguel Island, CA.
Photo by Kent Bullard, NREL 6325496



Photo by Michael Deru. NREL 10075381



Ballasted PV System on ESIF. Photo by Dennis Schroeder, NREL 13163640



# Solar Photovoltaics (PV) Fixed Tilt/Tracking




Fixed Tilt Facing Equator
tilt=latitude
tilt<latitude for summer gain
tilt>latitude for winter gain









Two Axis Tracking both azimuth and altitude of sun around two axes



# Total Area Required for PV

- Varies by technology, tilt, and location
- Roof mount sloped roof, flush-mounted power densities of 11 direct current (DC)-watt (W)/square foot (ft<sup>2</sup>) crystalline
- Flat roof, slope panel = 8 DC-W/ft<sup>2</sup>

Ground Mount			
System Type	Fixed Tilt Energy Density (DC-W/ft²)	Single Axis Tracking Energy Density (DC-W/ft²)	
Crystalline Silicon	4	3.3	
Thin Film	3.3	2.7	
Hybrid High Efficiency	4.8	3.9	



# Types of PV Cells

Single Crystal \* Multi-Crystal \* Thin Film \* Cadmium Telluride \* CIGS

Efficiencies: 

\* Multi-Crystal \* Thin Film \* Cadmium Telluride \* CIGS

\* CIGS

\* Thin Film \* Cadmium Telluride \* CIGS

10% to 11%

12% to 14%

13 to 17% 6 to 11%

14 to 23%

#### Solar Assessment: PV is VERY Shade Sensitive





Shade Analyzer

Once preliminary site assessment has been completed, you want to know:

- Estimated system size
- Estimated production (kilowatt-hour [kWh]/yr)
- Estimated cost
- Some economic analysis

# **PVWATTS Tool for Basic PV Modeling**

#### Free interactive map-based tool allows you to:

- Estimate expected monthly and annual solar resource values
- Quickly obtain performance estimates for grid-connected PV systems
- Get a first cut of potential solar output
- Can identify potential incentives that a PV system in a particular area may be eligible for

### **PVWATTS Calculator**

PVWatts® Calculator Calculator				CONREL NATIONAL RENEWABLE ENERGY LABORATORY		
My Location	42 S Washington Denv	er Co 80209	Beta Release ( ? )	HELP	FEEDBACK	ALL NREL SOLAR TOOLS
4		RESOURCE DATA SYSTEM IN	FO RESULTS			
	SYSTEM INFO  Modify the inputs below to r	un the simulation.		R	ESTORE DEFAULTS	
Go to	DC System Size (kW):	4	<b>a</b>	Dra	w Your Systen	Go to
	Array Type:	Fixed Tilt	0	cust	below to omize your	P
	DC-to-AC Derate Factor:	0.77	<b>a</b>		em on a map. onal)	
	Tilt (°):	39.7	<b>6</b>	٥	(Bap   Sente	
	Azimuth (°):	180	•	Coogle		
	ECONOMICS (Optional)					-
	Modify the inputs below to e	estimate the cost of energy produc	ed by the system.			
	System Type:	Residential	•			
	Utility Rate (\$):	0.09	•			
	Initial Cost (\$/Wdc):	6.00	<b>1</b>			

http://pvwatts.nrel.gov/



## Project Risk: Facility/Community-Scale Post Step 1

	Risks	Risk Assessment Post Step 1	✓
Development	Loss/waste of development resources	Low but rising; "calculated"	
Site	Improper orientation or project affected by shade	Reduced	$\checkmark$
	Inadequate foundation or structural integrity	Assumed low	<b>√</b>
	Site control challenges for safety/security purposes	Assumed low	<b>√</b>
Permitting	• Tribe-adopted codes and permitting requirements	Unchanged	
	Utility interconnection requirements	Unchanged	
Finance	Capital constraints	Assumed low	
	Incentive unavailability or insufficiency	Reduced	
Construction/ Completion	Engineering, procurement, and construction difficulties	Assumed low, mitigable, or allocatable	
	Cost overruns	Assumed low, mitigable, or allocatable	
	Schedule overruns	Assumed low, mitigable, or allocatable	
Operating	Output shortfall from expected	Assumed low, mitigable, or allocatable	
	Operations & maintenance (O&M) issues	Assumed low, mitigable, or allocatable	

NOTE: Underlining signifies that the risk assessment outcome changes during the step at hand.

Sources: Adapted from Holland & Hart, RE Project Development & Finance & Infocast, Advanced RE Project Finance & Analysis



# Activity

Resource Map/Siting

